



PC Cable Tester

PC Cable Tester Pro & ATA are the advanced version of the original PC Cable Tester. The Pro version provide with the USB and 1394 Firewire cable test, the ATA version supports a serial ATA attachment. PC Cable Tester ATA is capable of testing nearly every PC cable on the market.

PC Cable Tester is a stand-alone testing device designed to provide its users with a wiremap of standard PC data cables. Its unique LED display clearly determines wiring status by providing a pin-to-pin outline of the actual wiring configuration. PC Cable Tester can quickly and simply diagnose the existence of open wires, shorted wires, crossed wires, mis-wiring, and continuity.

Specifications

- Model No.: 258981
- Connectors: TX: DB25 M/F, DB9 M/F, HDB 15/M, RJ45/F, RX: Centronics 36/F, DB25 M/F, DB9 M/F, HD15/F, DB15F, RJ45/F
- Control switch: Wire numbers select x1; Auto/manual scanning switch x1; Power on/off switch x1. Test x1 (for manual operation); Scanning speed high/low switch x1.
- Display: TX: 25 LEDs; Battery low x1; 4 sections wires selection (for 4, 9, 15, 25). RX: 36LEDs; Ground Tx Ground RX.
- Battery: DC 9V battery compartment; DC 9V 150mA power jack
- Dimensions: 250 x 130 x 35mm
- Weight: 400g

Order information

interface model no.	BNC female	USB socket	1394 socket	series ATA
258981	yes	no	no	no
258991	yes	yes	yes	no
258991A	no	yes	yes	yes